



# Single-Output: 500 W GPIB



6651A-6655A

- Increase test throughput with fast up and down programming time
- Protect valuable assemblies with fast protection features
- Proven reliability
- Low ripple and noise

This series of 500 W linear-regulated dc power supplies is designed to maximize the throughput of DUTs through the manufacturing test process with fast up and down programming time.

Valuable assemblies can be destroyed by a minor component failure that causes a surge of current to flow into the DUT. Fast protection features, including fast crowbar, mode crossover protection, and the ability to connect the protection circuitry of multiple power supplies can increase production yield.

Programming of the dc output and the protection features can be done either from the front panel or using industry standard SCPI commands, via the GPIB. Using the serial link, up to 16 power supplies can be connected through one GPIB address. Test system integration can be further simplified by using the *VXIPlug&Play* drivers. The output voltage and current can also be controlled with analog signals. This is helpful for certain types of noisy environments, and also immediate reactions to process changes.

Lab bench use is enhanced by the fan speed control, which helps to minimize the acoustic noise.

Specifications (at 0° to 55° C unless otherwise specified)	6651A	6652A	6653A	6654A	6655A	6651A-J01 Special Order Option
<b>Number of outputs</b>	1	1	1	1	1	1
<b>GPIB</b>	Yes	Yes	Yes	Yes	Yes	Yes
<b>Output ratings</b>						
Output voltage	0 to 8 V	0 to 20 V	0 to 35 V	0 to 60 V	0 to 120 V	10 V
Output current (40° C)	0 to 50 A	0 to 25 A	0 to 15 A	0 to 9 A	0 to 4 A	50 A
Maximum current (50° C/55° C)	45 A/42.5 A	22.5 A/21.3 A	13.5 A/12.8 A	8.1 A/7.7 A	3.6 A/3.4 A	45 A/42.5 A
<b>Programming accuracy at 25° C ±5° C</b>						
Voltage	0.06% + 5 mV	10 mV	15 mV	26 mV	51 mV	6 mV
Current	0.15% + 60 mA	25 mA	13 mA	8 mA	4 mA	60 mA
<b>Ripple and noise</b> from 20 Hz to 20 MHz						
Voltage rms	300 µV	300 µV	400 µV	500 µV	700 µV	300 µV
peak-peak	3 mV	3 mV	4 mV	5 mV	7 mV	3 mV
Current rms	25 mA	10 mA	5 mA	3 mA	2 mA	25 mA
<b>Readback accuracy at 25° C ±5° C</b> (percent of reading plus fixed) System models only						
Voltage	0.07% + 6 mV	15 mV	25 mV	40 mV	80 mV	7.5 mV
+Current	0.15% + 67 mA	26 mA	15 mA	7 mA	3 mA	67 mA
-Current	0.35% + 100 mA	44 mA	24 mA	15 mA	7 mA	100 mA
<b>Load regulation</b>						
Voltage	1 mV	2 mV	3 mV	4 mV	5 mV	1 mV
Current	2 mA	1 mA	0.5 mA	0.5 mA	0.5 mA	2 mA
<b>Line regulation</b>						
Voltage	0.5 mV	0.5 mV	1 mV	1 mV	2 mV	0.5 mV
Current	2 mA	1 mA	0.75 mA	0.5 mA	0.5 mA	2 mA
<b>Transient response time</b>	Less than 100 µs for the output voltage to recover to its previous level (within 0.1% of the voltage rating of the supply or 20 mV, whichever is greater) following any step change in load current of up to 50% of rated current					
<b>Supplemental Characteristics</b>	(Non-warranted characteristics determined by design and useful in applying the product)					
<b>Average resolution</b>						
Voltage	2 mV	5 mV	10 mV	15 mV	30 mV	2.5 mV
Current	15 mA	7 mA	4 mA	2.5 mA	1.25 mA	15 mA
OVP	12 mV	30 mV	54 mV	93 mV	190 mV	16 mV
OVP accuracy	160 mV	400 mV	700 mV	1.2 V	2.4 V	200 mV



## Single-Output: 500 W GPIB (Continued)

### Supplemental Characteristics for all model numbers

**dc Floating Voltage:** Output terminals can be floated up to  $\pm 240$  Vdc from chassis ground

**Remote Sensing:** Up to half the rated output voltage can be dropped in each load lead. The drop in the load leads subtracts from the voltage available for the load.

**Command Processing Time:** Average time required for the output voltage to begin to change following receipt of digital data is 20 ms for the power supplies connected directly to the GPIB

**Output Programming Response Time:** The rise and fall time (10/90% and 90/10%) of the output voltage is less than 15 ms. The output voltage change settles within 1 LSB (0.025% x rated voltage) of final value in less than 60 ms.

**Down Programming:** An active down programmer sinks approximately 20% of the rated output current

**Modulation:** (Analog programming of output voltage and current)

Input signal: 0 to -5 V

Input impedance: 10 k Ohm nominal

**ac Input:** (ac input frequency 47 to 63 Hz)  
**Voltage** 100 Vac 120 Vac 220 Vac 240 Vac  
**Current** 12 A 10 A 5.7 A 5.3 A

**Input Power:** 1,380 VA, 1,100 W at full load; 120 W at no load

**GPIB Interface Capabilities:** SH1, AH1, T6, L4, SR1, RL1, PP0, DC1, DT1, E1, and C0. IEEE-488.2 and SCPI-compatible command set.

**Regulatory Compliance:** Listed to UL 1244; conforms to IEC 61010-1.

**Size:** 425.5 mm W x 132.6 mm H x 497.8 mm D (16.75 in x 5.22 in x 19.6 in)  
 See page 101 for more details

**Weight:** Net, 25 kg (54 lb); shipping, 28 kg (61 lb)

**Warranty Period:** One year

Specifications (at 0° to 55° C unless otherwise specified)	6651A-J03 Special Order Option	6651A-J09 Special Order Option	6652A-J03 Special Order Option	6653A-J04 Special Order Option	6653A-J17 Special Order Option
<b>Number of outputs</b>	1	1	1	1	1
<b>GPIB</b>	Yes	Yes	Yes	Yes	Yes
<b>Output ratings</b>					
Output voltage	6 V	17V/20 V	27 V	40 V	30 V
Output current (40° C)	60 A	30 A/15 A	18.5 A	12.5 A	17.5 A
Maximum current (50° C/55° C)	54 A/5 1A	27 A/25.5 A 13.5 A/12.75 A	16.65 A/15.72 A	11.25 A/10.6 A	15.75 A/14.87 A
<b>Programming accuracy at 25° C <math>\pm</math> 5° C</b>					
Voltage	0.06% +	5 mV	10 mV	13.5 mV	17.5 mV
Current	0.15% +	75 mA	36 mA	25 mA	13 mA
<b>Ripple and noise</b>					
from 20 Hz to 20 MHz					
Voltage rms	300 $\mu$ V	300 $\mu$ V	450 $\mu$ V	1.6 mV	400 $\mu$ V
peak-peak	3 mV	4 mV	4.5 mV	5 mV	4 mV
Current rms	30 mA	13 mA	10 mA	5 mA	6 mA
<b>Readback accuracy at 25° C <math>\pm</math> 5° C</b> (percent of reading plus fixed) System models only					
Voltage	0.07% +	6 mV	15 mV	20.5 mV	30 mV
+Current	0.15% +	80 mA	40 mA	26 mA	15 mA
-Current	0.35% +	150 mA	55 mA	44 mA	24 mA
<b>Load regulation</b>					
Voltage	1 mV	2 mV	2 mV	3.5 mV	3 mV
Current	6.5 mA	2 mA	1 mA	1 mA	0.5 mA
<b>Line regulation</b>					
Voltage	0.5 mV	0.5 mV	0.5 mV	1 mV	1 mV
Current	2 mA	2 mA	2 mA	0.75 mA	0.75 mA
<b>Transient response time</b>	Less than 100 $\mu$ s for the output voltage to recover to its previous level (within 0.1% of the voltage rating of the supply or 20 mV, whichever is greater) following any step change in load current of up to 50% of rated current				
<b>Supplemental Characteristics</b> (Non-warranted characteristics determined by design and useful in applying the product)					
<b>Average resolution</b>					
Voltage	2 mV	5 mV	6.75 mV	12mV	10 mV
Current	18 mA	9 mA	7 mA	4 mA	5 mA
OVP	12 mV	30 mV	30 mV	65 mV	54 mV
OVP accuracy	160 mV	500 mV	400 mV	750 mV	700 mV



## Single-Output: 500 W GPIB (Continued)

### Ordering Information

- Opt 100 87 to 106 Vac, 47 to 63 Hz
- Opt 120 104 to 127 Vac, 47 to 63 Hz
- Opt 220 191 to 233 Vac, 47 to 63 Hz
- Opt 240 209 to 250 Vac, 47 to 63 Hz
- \* Opt 908 Rack-mount Kit (p/n 5062-3977)
- \* Opt 909 Rack-mount Kit w/ Handles (p/n 5063-9221)
- Opt 0L2 Extra Standard Documentation Package
- Opt 0B3 Service Manual
- Opt 0B0 No documentation package

\* Support rails required

### Accessories

- p/n 1494-0059 Accessory Slide Kit
- p/n 1252-3698 7-pin Analog Plug
- p/n 1252-1488 4-pin Digital Plug
- p/n 5080-2148 Serial Link Cable 2 m (6.6 ft)
- E3663AC Support rails for Agilent rack cabinets

Specifications (at 0° to 55° C unless otherwise specified)	6654A-J04 Special Order Option	6654A-J05 Special Order Option	6654A-J12 Special Order Option	6655A-J05 Special Order Option	6655A-J10 Special Order Option
<b>Number of outputs</b>	1	1	1	1	1
<b>GPIB</b>	Yes	Yes	Yes	Yes	Yes
<b>Output ratings</b>					
Output voltage	70 V	50 V	80 V	150 V	156 V
Output current (40° C)	7.5 A	10 A	6 A	3.2 A	3 A
Maximum current (50° C/55° C)	6.75 A/6.37 A	9 A/8.5 A	5.4 A/5.1 A	2.88 A/2.72 A	2.7 A/2.55 A
<b>Programming accuracy at 25° C ±5° C</b>					
Voltage	0.06% +	30 mV	26 mV	35 mV	64 mV
Current	0.15% +	7 mA	9 mA	7 mA	3.5 mA
<b>Ripple and noise from 20 Hz to 20 MHz</b>					
Voltage rms	600 µV	500 µV	700 µV	800 µV	900 µV
peak-peak	6 mV	5 mV	7 mV	8 mV	8 mV
Current rms	5 mA	4 mA	3 mA	2 mA	3 mA
<b>Readback accuracy at 25° C ±5° C (percent of reading plus fixed) System models only</b>					
Voltage	0.07% +	50 mV	40 mV	58 mV	100 mV
+Current	0.15% +	6 mA	8 mA	6 mA	2.5 mA
-Current	0.35% +	13 mA	17 mA	16 mA	6.5 mA
<b>Load regulation</b>					
Voltage	4 mV	4 mV	4 mV	6 mV	7 mV
Current	0.5 mA	0.5 mA	0.5 mA	0.5 mA	1 mA
<b>Line regulation</b>					
Voltage	1 mV	1 mV	4.5 mV	2 mV	2 mV
Current	0.5 mA	0.5 mA	0.5 mA	0.5 mA	1 mA
<b>Transient response time</b>	Less than 100 µs for the output voltage to recover to its previous level (within 0.1% of the voltage rating of the supply or 20 mV, whichever is greater) following any step change in load current of up to 50% of rated current				
<b>Supplemental Characteristics</b>					
(Non-warranted characteristics determined by design and useful in applying the product)					
<b>Average resolution</b>					
Voltage	17.5 mV	15 mV	20 mV	37.5 mV	39.5 mV
Current	1.9 mA	2.75 mA	1.7 mA	8 mA	8 mA
OVP	110 mV	93 mV	130 mV	240 mV	250 mV
OVP accuracy	1.4 V	1.2 V	1.6 V	3 V	3.3 V

### Your Requested Excerpt from the Agilent Power Products Catalog

The preceding page(s) are an excerpt from the *2002-2003 Power Products Catalog*.

We hope that these pages supply the information that you currently need.

If you would like to have further information about the extensive selection of Agilent dc power supplies, ac sources, and dc electronic loads, please visit [www.agilent.com/find/power](http://www.agilent.com/find/power) to print a copy of the complete Power Products catalog, or to request that a copy be sent to you. You will also find a lot of other useful information on this web site.

In the full Power Products Catalog, you will find that Agilent offers much more than basic power generation. If you need basic, clean, power for your lab bench, it's there. But in each product category, we've also integrated the capabilities that you need for a complete power solution, including extensive measurement and analysis capabilities.

Please give us a call at your local Agilent Technologies sales office, or call a regional office listed below, for assistance in choosing or using Agilent power products.

### Keep up to date with Agilent's Test and Measurement Email Updates

As an Email Update subscriber, you will receive periodic customized email updates that match the areas of interest that you have specified. Your update will include products and services, applications and support information, events, and promotions. Sign up today at [www.agilent.com/find/emailupdates](http://www.agilent.com/find/emailupdates).

Check off dc power supplies, ac power sources or electronic loads on your registration form, and we will promptly let you know what's new in power products! Our Privacy Statement at [www.agilent.com/go/privacy](http://www.agilent.com/go/privacy) describes our commitment to you regarding your privacy.

To see a copy of the user's guide, please visit our Web site at [www.agilent.com/find/manuals](http://www.agilent.com/find/manuals)

By internet, phone, or fax, get assistance with all your test & measurement needs

Online assistance:  
[www.agilent.com/find/assist](http://www.agilent.com/find/assist)

### Phone or Fax

**United States:**  
(tel) 1 800 829 4444

**Canada:**  
(tel) 1 877 894 4414  
(fax) (905) 282-6495

**China:**  
(tel) 800-810-0189  
(fax) 1-0800-650-0121

**Europe:**  
(tel) (31 20) 547 2323  
(fax) (31 20) 547 2390

**Japan:**  
(tel) (81) 426 56 7832  
(fax) (81) 426 56 7840

**Korea:**  
(tel) (82-2) 2004-5004  
(fax) (82-2) 2004-5115

**Latin America:**  
(tel) (305) 269 7500  
(fax) (305) 269 7599

**Taiwan:**  
(tel) 080-004-7866  
(fax) (886-2) 2545-6723

**Other Asia Pacific Countries:**  
(tel) (65) 375-8100  
(fax) (65) 836-0252  
Email: [tm\\_asia@agilent.com](mailto:tm_asia@agilent.com)

Product specifications and descriptions in this document subject to change without notice.