



home | about | products | applications | news | service & support | global sales | careers | faq | contact

Peak Power Meters | RF Power Meters | Spectrum Analyzers | RF Volt Meters | Capacitance Meters | Modulation Analyzers | Audio Analyzers

[SITE MAP](#)

Products

**Peak Power Meters**

**RF Power Meters**

**Spectrum Analyzers**

**RF Volt Meters**

**Capacitance Meters**

**Modulation Analyzers**

**Audio Analyzers**

**Peak Power Sensors**

**CW Sensors**

**Peak Power Sensors**

Model	Frequency Range (Low Bandwidth)	Dynamic Range Peak Pwr Rng CW Pwr Rng(1) Int Trigger Range	Overload Rating Pulse / Continuous	Sensor Response Fast Risetime (Bandwidth) Slow Risetime (Bandwidth)	Maximum SWR Frequency SWR
-------	---------------------------------	--	------------------------------------	---	---------------------------

**PEAK POWER SENSORS**

For use with models 4500B only.

56006 50 ohm N (M)	0.5 - 6 GHz	-50 to +20 dBm -60 to +20 dBm -40 to +20 dBm	1 W for 1µs 200 mW	<7 nsec (65 MHz typical)	N/A	0.5 - 6 GHz 1.25
58318 50 ohm N (M)	0.5 - 18 GHz	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1µs 200 mW	<10 nsec (50 MHz typical)	N/A	0.5 - 2 GHz 2 - 6 GHz 6 - 16 GHz 16 - 18 GHz 1.15 1.20 1.28 1.34

For use with models 4400, 4500, 4400A, and 4500A and 4500B Analyzers and 4530 Series RF Power Meter when combined with Model 2530 1 GHz calibrator accessory.

56218 50 ohm N (M)	0.03 - 18 GHz	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1µs 200 mW	<150 ns (2 MHz)	<500 ns (700 kHz)	0.03 - 1 GHz 1 - 6 GHz 6 - 18 GHz 1.15 1.20 1.25
56318 50 ohm N (M)	0.5 - 18 GHz	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1µs 200 mW	<15 ns (2) (35 MHz)	<200 ns (1.75 MHz)	0.5 - 1 GHz 1 - 6 GHz 6 - 16 GHz 16 - 18 GHz 1.15 1.20 1.28 1.34
56326 50 ohm K (M)	0.5 - 26.5 GHz	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1µs 200 mW	<15 ns(2) (35 MHz)	<200 ns (1.75 MHz)	0.5 - 1 GHz 1 - 4 GHz 4 - 18 GHz 18 - 26.5 GHz 1.15 1.20 1.45 1.50
56518 50 ohm N (M)	0.5 - 18 GHz	-40 to +20 dBm -50 to +20 dBm -27 to +20 dBm	1 W for 1µs 200 mW	<100 ns (6 MHz)	<300 ns (1.16 MHz)	0.5 - 1 GHz 1 - 6 GHz 6 - 16 GHz 16 - 18 GHz 1.15 1.20 1.28 1.34

For use with models 4400, 4500, 4400A, 4500A, 4500B and 4530. Compatible with 4530 Series internal 50 MHz calibrator.

57318 50 ohm N (M)	0.5 - 18 GHz (0.05 - 18 GHz)	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1µs 200 mW	<15 ns(2) (35 MHz)	<10 µs (350 kHz)	0.05 - 2 GHz 2 - 6 GHz 6 - 16 GHz 16 - 18 GHz 1.15 1.20 1.28 1.34
57340 50 ohm K (M)	0.5 - 40 GHz (0.05 - 40 GHz)	-24 to +20 dBm -34 to +20 dBm -10 to +20 dBm	1 W for 1µs 200 mW	<15 ns(2) (35 MHz)	<10 µs (350 kHz)	0.05 - 4 GHz 4 - 38 GHz 38 - 40 GHz 1.25 1.65 2.00
57518 50 ohm N (M)	0.1 - 18 GHz (0.05 - 18 GHz)	-40 to +20 dBm -50 to +20 dBm -27 to +20 dBm	1 W for 1µs 200 mW	<100 ns (6 MHz)	<10 µs (350 kHz)	0.05 - 2 GHz 2 - 6 GHz 6 - 16 GHz 16 - 18 GHz 1.15 1.20 1.28 1.34
57540 50 ohm K (M)	0.1 - 40 GHz (0.05 - 40 GHz)	-40 to +20 dBm -50 to +20 dBm -27 to +20 dBm	1 W for 1µs 200 mW	<100 ns (6 MHz)	<10 µs (350 kHz)	0.05 - 4 GHz 4 - 38 GHz 38 - 40 GHz 1.15 1.65 2.00

[Go to Top](#)