


# Keysight Technologies

## Pulse Analysis

### X-Series Measurement App, Multi-Touch

#### N9067C

## Technical Overview



- Automatically synchronize to pulse modulated signals for radar and electronic warfare (EW) applications up to 50 GHz and bandwidth of 510 MHz
- Verify all key pulse signal modulation performance indicators relating to power, droop, overshoot, ripple, time (rise/fall/width/PRI), frequency, phase, and FM modulation using the comprehensive pulse table result metrics
- Integrates with popular real-time instrument functionality (UXA, PXA, MXA) such as frequency mask trigger
- Select from five X-Series signal analyzers with multi-touch to meet your specific design and test goals
- Use multi-touch front panel user interface or SCPI remote control
- Extend test assets with transportable licenses between all X-Series signal analyzers with multi-touch UI

## Pulse Analysis Measurement Application

The Keysight Technologies, Inc. N9067C pulse analysis measurement application for multi-touch signal analyzers provides pulsed radar and electronic warfare (EW) analysis to characterize today's dynamic signal environment. In mission-critical aerospace, defense and EW applications, signal design and validation require comprehensive tools for pulsed radar signal analysis and cross-domain - time, frequency and modulation - test capabilities. To help engineers achieve their design validation goals, the N9067C, a powerful multi-touch application, integrates with the powerful multi-touch X-Series signal analyzers for comprehensive analysis and troubleshooting. The N9067C populates a diverse set of pulse metrics in a flexible table format. All metrics, including pulse table results, result statistics, and cumulative statistics are easily saved into formats such as .csv for custom reports and post analysis.

### X-Series measurement applications

X-Series measurement applications increase the capability and functionality of Keysight signal analyzers to speed time to insight. They provide essential measurements for specific tasks in general-purpose, cellular communications, wireless connectivity and digital video applications, covering established standards and modulation types. Applications are supported across X-Series signal analyzers, with the only difference being the level of performance achieved by the hardware you select.

## Download your next insight

Keysight software is downloadable expertise. From first simulation through first customer shipment, we deliver the tools your team needs to accelerate from data to information to actionable insight.

- Electronic design automation (EDA) software
- Application software
- Programming environments
- Productivity software



Start with a 30-day free trial.

[www.keysight.com/find/X-Series\\_trial](http://www.keysight.com/find/X-Series_trial)




Figure 1. The N9067C pulse analysis measurement application provides a user interface designed to make quick pulse measurements.

## Top Features

- Verify all key pulse signal modulation performance indicators relating to power, droop, overshoot, ripple, time (rise/fall/width/PRI), frequency, phase, and FM modulation using the comprehensive pulse table result metrics
- Visualize pulse signal modulation characteristics and impairment errors in detail with multiple time-synchronized amplitude, phase, and frequency (FM) trace results, in addition to flexible trace overlay support
- Quickly view statistical variance performance data for each reported pulse metric, accumulated over single or multiple acquisitions, using the pulse cumulative statistics table, graphical histogram, and trend line trace plots
- Gain deeper insights into your signal's time and frequency domain dynamic and spurious performance with powerful and flexible trace views such as spectrogram and cumulative history

## Pulse analysis in spectrum and time domain with one tool

Traditionally, pulsed RF signals have been designed by radar and EW system engineers using a spectrum analyzer for frequency domain characteristics and oscilloscopes for time domain characteristics. Making other frequency and time domain measurements with exactly the same time-sampled data is one of the simplest, yet most important, vector signal analysis techniques. This is especially true when characterizing transient or non-stationary signals such as complex pulsed RF signals in aerospace and defense applications. The pulse analysis application provides simple setup for pulse detection, comprehensive pulse analysis parameters in various traces with visualization and reporting of test results.




Figure 2. Simultaneous views of pulse signals versus time.

## Quickly transition from real-time spectrum analysis to pulse analysis

The indispensable real-time trigger capability offered by the RTSA measurement functionality has been integrated into the N9067C pulse analysis measurement application metrics. Using the multi-window capability, going between 510 MHz real-time analysis and automatic pulse measurements has never been easier.




Figure 3. Simultaneous views of pulse magnitude, real-time response and cumulative statistics.

## Results, statistics & automation

With the N9067C, you can calculate amplitude, time, phase, and frequency, for analog troubleshooting, identification of integration issues and even full system algorithm test. The proprietary high dynamic range wideband ADC built into the UXA and PXA, enables the N9067C to simultaneously determine fast rise/fall times and amplitude parameters such as pulse droop, for cross domain analysis across the entire channel. For example, if there is modulation on pulse, the N9067C can determine the linearity of a chirped signal, auto-detect coding (such as Barker) and display phase shifts in the pulse. Additionally, ECCM activity such as frequency hopping can be measured with each incoming pulse. Using a frequency mask trigger (FMT), the trigger can be initiated at any desired time during the hop sequence.

When analyzing a long data capture, the N9067C can help you identify different pulse modes with time qualified triggers, making troubleshooting a much faster process. The statistics and histograms plots can be used over large acquisition bandwidth to find intermittent issues or verify algorithms over long periods of time.




Figure 4. Specify results view from extensive list of parameters.




Figure 5. Easily measure pulse linearity and use qualified trigger to select appropriate signal to analyzer.

## Measurement Summary

Category	Measurements	Result/Parameter
Amplitude	Amplitude error time, amplitude meas time, amplitude ref time	
Phase	Phase error time, phase meas time, phase ref time	
FM	FM error spectrum, FM error time, FM meas spectrum, FM meas time, FM ref spectrum, FM ref time	
Pulse result table	Level (in dBm, unless otherwise noted)	Top level, base level, top/base ratio (dB), on level, peak level, mean level, peak to average (dB)
	Droop	Droop (%), droop (dB), droop rate (dB/us), droop start (dBm), droop stop (dBm)
	Overshoot	Overshoot (%), overshoot (dB)
	Ripple	Ripple (%), ripple (dB)
	Time (in seconds, unless otherwise noted)	Rise time, rising edge, fall time, falling edge, width, off time, PRI, PRF (Hz), duty cycle (%)
	Frequency (in Hz, unless otherwise noted)	Freq mean, freq pulse-pulse difference, freq pk-pk deviation, freq error time, freq error peak, freq error peak location (sec)
	Phase (in degrees, unless otherwise noted)	Phase mean, phase pulse-pulse difference, phase pk-pk deviation, phase error rms, phase error peak, phase error peak location (sec)
	Best-fit FM (in Hz, unless otherwise noted)	Best-fit FM mean, best-fit FM start, best-fit FM stop, best-fit FM pk-pk deviation, best-fit FM slope (Hz/ $\mu$ sec), best-fit FM INL (%), integral non linearity)
Current statistics table	Same as above results with Min, Max, RMS, Average, Std Dev, Count	
Cumulative statistics table	Same as above results with Min, Max, RMS, Average, Std Dev, Count, Median, Mode	

## Key Specifications

### Nominal definition

Nominal values are designated with the abbreviation “nom.” These values indicate expected performance, or describe product performance that is useful in the application of the product, but is not covered by the product warranty. Note: data is subject to change.

<b>Accuracy - Amplitude and timing</b>	<b>PXA (N9030B)</b>	<b>UXA (N9040B)</b>
<b>Description</b>	<b>Nominal</b>	<b>Nominal</b>
Top level <sup>1</sup>	±0.2 dB + Absolute amplitude accuracy (CW) ±0.2 dB + Absolute amplitude accuracy + IF frequency response (chirp)	
On level <sup>1</sup>	±0.1 dB + Absolute amplitude accuracy (CW) ±0.1 dB + Absolute amplitude accuracy + IF frequency response (chirp)	
Mean level <sup>1</sup>	±0.1 dB + Absolute amplitude accuracy (CW) ±0.1 dB + Absolute amplitude accuracy + IF frequency response (chirp)	
Peak level <sup>1</sup>	±0.2 dB + Absolute amplitude accuracy (CW) ±0.2 dB + Absolute amplitude accuracy + IF frequency response (chirp)	
Width <sup>1</sup>	±1/Sample rate	
PRI <sup>1</sup>	±1/Sample rate	
<b>Accuracy - Frequency and phase CW (non-chirp signal)</b>	<b>PXA (N9030B)</b>	<b>UXA (N9040B)</b>
<b>Frequency error RMS <sup>2,3</sup></b>		
CF 2 GHz		
Option B40	±1.6 kHz	±1.6 kHz
Option B85	±3.5 kHz	
Option B1X	±8.3 kHz	
Option B2X		±21 kHz
Option B5X		±62 kHz
CF 10 GHz		
Option B40	±3.5 kHz	±3.5 kHz
Option B85	±5.4 kHz	
Option B1X	±13 kHz	
Option B2X		±31 kHz (±18 kHz <sup>4</sup> )
Option B5X		±87 kHz (±110 kHz <sup>4</sup> )
CF 20 GHz		
Option B40	±5.9 kHz	±5.9 kHz
Option B85	±5.9 kHz	
Option B1X	±5.9 kHz	
Option B2X		±52 kHz (±17 kHz <sup>4</sup> )
Option B5X		±150 kHz (±88 kHz <sup>4</sup> )

1. SNR ≥ 30 dB, pulse width ≥ 100/bandwidth
2. ATT = 0 dB. IF gain = low, signal condition with pulse on power = -10 dBm and pulse width ≥ 100/bandwidth, modulation setup with FM filter bandwidth = 10%
3. Frequency/phase analysis setup width = 50%
4. Pulse to pulse analysis setup: reference time = center, offset = 0.0 s, window length = 0.0 s

	PXA (N9030B)	UXA (N9040B)
<b>Frequency pulse to pulse difference <sup>1,2</sup></b>		
CF 2 GHz		
Option B40	±3.3 kHz	±3.3 kHz
Option B85	±7.1 kHz	
Option B1X	±17 kHz	
Option B2X		±47 kHz
Option B5X		±130 kHz
CF 10 GHz		
Option B40	±7.4 kHz	±7.4 kHz
Option B85	±12 kHz	
Option B1X	±26 kHz	
Option B2X		±62 kHz (±22 kHz <sup>2</sup> )
Option B5X		±180 kHz (±56 kHz <sup>2</sup> )
CF 20 GHz		
Option B40	±13 kHz	±13 kHz
Option B85	±23 kHz	
Option B1X	±52 kHz	
Option B2X		±110 kHz (±30 kHz <sup>2</sup> )
Option B5X		±290 kHz (±68 kHz <sup>2</sup> )
<b>Phase pulse to pulse difference <sup>1,2</sup></b>		
CF 2 GHz		
Option B40	±0.3°	±0.3°
Option B85	±0.3°	
Option B1X	±0.3°	
Option B2X		±0.3°
Option B5X		±0.6°
CF 10 GHz		
Option B40	±0.7°	±0.7°
Option B85	±0.7°	
Option B1X	±0.7°	
Option B2X		±0.45° (±0.3° <sup>2</sup> )
Option B5X		±0.6° (±0.3° <sup>2</sup> )
CF 20 GHz		
Option B40	±1.3°	±1.3°
Option B85	±1.3°	
Option B1X	±1.3°	
Option B2X		±0.75° (±0.55° <sup>2</sup> )
Option B5X		±1.1° (±0.55° <sup>2</sup> )

1. ATT = 0 dB. IF gain = low, signal condition with pulse on power = -10 dBm and pulse width ≥ 100/bandwidth, modulation setup with FM filter bandwidth = 10%
2. Pulse to pulse analysis setup: reference time = center, offset = 0.0 s, window length = 0.0 s



Accuracy - Frequency and Phase Chirp (Linear Chirp Signal)	PXA (N9030B)	UXA (N9040B)
<b>Frequency Error RMS <sup>1,2</sup></b>		
CF 2 GHz		
Option B40	±3.5 kHz	±3.5 kHz
Option B85	±6 kHz	
Option B1X	±15 kHz	
Option B2X		±21 kHz
Option B5X		±87 kHz
CF 10 GHz		
Option B40	±5 kHz	±5 kHz
Option B85	±12 kHz	
Option B1X	±25 kHz	
Option B2X		±31 kHz
Option B5X		±87 kHz
CF 20 GHz		
Option B40	±7.5 kHz	±7.5 kHz
Option B85	±20 kHz	
Option B1X	±35 kHz	
Option B2X		±55 kHz
Option B5X		±150 kHz
<b>Frequency pulse to pulse difference <sup>1,3</sup></b>		
CF 2 GHz		
Option B40	±3.5 kHz	±3.5 kHz
Option B85	±7.3 kHz	
Option B1X	±17 kHz	
Option B2X		±47 kHz
Option B5X		±140 kHz
CF 10 GHz		
Option B40	±7 kHz	±7 kHz
Option B85	±15 kHz	
Option B1X	±30 kHz	
Option B2X		±70 kHz
Option B5X		±200 kHz
CF 20 GHz		
Option B40	±12 kHz	±12 kHz
Option B85	±25 kHz	
Option B1X	±60 kHz	
Option B2X		±125 kHz
Option B5X		±320 kHz

1. ATT = 0 dB. IF gain = low, signal condition with pulse on power = -10 dBm and pulse width  $\geq 100/\text{bandwidth}$ , modulation setup with FM filter bandwidth = 10%
2. Frequency/phase analysis setup width = 50%
3. Pulse to pulse analysis setup: reference time = center, offset = 0.0 s, window length = 0.0 s

<b>Accuracy - frequency and phase chirp (linear chirp signal), continued</b>		
<b>Phase pulse to pulse difference <sup>1,2</sup></b>	<b>PXA (N9030B)</b>	<b>UXA (N9040B)</b>
<b>CF 2 GHz</b>		
Option B40	±0.35°	±0.35°
Option B85	±0.35°	
Option B1X	±0.4°	
Option B2X		±0.3°
Option B5X		±0.45°
<b>CF 10 GHz</b>		
Option B40	±0.7°	±0.7°
Option B85	±0.7°	
Option B1X	±0.9°	
Option B2X		±0.5°
Option B5X		±0.6°
<b>CF 20 GHz</b>		
Option B40	±1°	±1°
Option B85	±1.2°	
Option B1X	±1.5°	
Option B2X		±1.0°
Option B5X		±1.2°

1. ATT = 0 dB. IF gain = low, signal condition with pulse on power = -10 dBm and pulse width ≥ 100/bandwidth, modulation setup with FM filter bandwidth = 10%
2. Pulse to pulse analysis setup: reference time = center, offset = 0.0 s, window length = 0.0 s

For a complete list of specifications, refer to the appropriate specifications guide:

UXA: [www.keysight.com/find/uxa\\_specifications](http://www.keysight.com/find/uxa_specifications)  
 PXA: [www.keysight.com/find/pxa\\_specifications](http://www.keysight.com/find/pxa_specifications)  
 MXA: [www.keysight.com/find/mxa\\_specifications](http://www.keysight.com/find/mxa_specifications)  
 EXA: [www.keysight.com/find/exa\\_specifications](http://www.keysight.com/find/exa_specifications)  
 CXA: [www.keysight.com/find/cxa\\_specifications](http://www.keysight.com/find/cxa_specifications)

## Ordering Information

### Software Licensing and Instrument Configuration

Choose from two license types::

- **Fixed, perpetual license:**  
This allows you to run the application in the X-Series analyzer in which it is initially installed.
- **Transportable, perpetual license:**  
This allows you to run the application in the X-Series analyzer in which it is initially installed, plus it may be transferred from one multi-touch X-Series analyzer to another.

### You Can Upgrade!

Options can be added after your initial purchase. All of our X-Series application options are license-key upgradeable.



For more information, please visit [www.keysight.com/find/n9067c](http://www.keysight.com/find/n9067c)

### Pulse analysis measurement application

Model-Option	Description, license type
N9067C-1FP <sup>1</sup>	Pulse analysis measurement application, fixed perpetual license
N9067C-1TP <sup>1</sup>	Noise figure measurement transportable perpetual

1. N9067C application requires an X-Series signal analyzer with multi-touch user interface. For more information, see hardware configurations.

## Hardware Configuration

For optimizing noise figure measurements with noise figure measurement application, Keysight recommends a minimum level of X-Series multi-touch signal analyzer hardware functionality at each instrument performance point.



Supported analyzers include:

- UXA N9040B
- PXA N9030B
- MXA N9020B
- EXA N9010B
- CXA N9000B

Capability	Instrument Option	Benefit
Analysis bandwidth	25 MHz minimum (-B25) or wider	Required: Wider analysis bandwidth to support enhanced sample interval, time resolution, rise/fall time and minimum pulse width
Microwave pre-selector by-pass	-MPB	Required : When input frequency is > 3.6 GHz on bandwidths 40 MHz or greater
Real-time spectrum analyzer	-RT1 or -RT2	Required: Detect signals as short as 3.33 ns with 100% POI
Frequency mask trigger	-FT1 or -FT2	Required: Focus on the signal of interest in a complex signal environment
Pre-amplifier	3.6 GHz (-P03) or higher	Recommended: For maximizing the measurement sensitivity
Fine resolution step attenuator	-FSA on EXA and CXA only	Recommended: Useful for maximizing useable dynamic range to see signals

## From Hewlett-Packard through Agilent to Keysight

For more than 75 years, we've been helping you unlock measurement insights. Our unique combination of hardware, software and people can help you reach your next breakthrough. **Unlocking measurement insights since 1939.**



For more information on Keysight Technologies' products, applications or services, please contact your local Keysight office. The complete list is available at: [www.keysight.com/find/contactus](http://www.keysight.com/find/contactus)

### Americas

Canada	(877) 894 4414
Brazil	55 11 3351 7010
Mexico	001 800 254 2440
United States	(800) 829 4444

### Asia Pacific

Australia	1 800 629 485
China	800 810 0189
Hong Kong	800 938 693
India	1 800 11 2626
Japan	0120 (421) 345
Korea	080 769 0800
Malaysia	1 800 888 848
Singapore	1 800 375 8100
Taiwan	0800 047 866
Other AP Countries	(65) 6375 8100

### Europe & Middle East

Austria	0800 001122
Belgium	0800 58580
Finland	0800 523252
France	0805 980333
Germany	0800 6270999
Ireland	1800 832700
Israel	1 809 343051
Italy	800 599100
Luxembourg	+32 800 58580
Netherlands	0800 0233200
Russia	8800 5009286
Spain	800 000154
Sweden	0200 882255
Switzerland	0800 805353
	Opt. 1 (DE)
	Opt. 2 (FR)
	Opt. 3 (IT)
United Kingdom	0800 0260637

For other unlisted countries:  
[www.keysight.com/find/contactus](http://www.keysight.com/find/contactus)  
 (BP-02-10-16)



[www.keysight.com/go/quality](http://www.keysight.com/go/quality)  
 Keysight Technologies, Inc.  
 DEKRA Certified ISO 9001:2015  
 Quality Management System

### myKeysight

**myKeysight**  
[www.keysight.com/find/mykeysight](http://www.keysight.com/find/mykeysight)  
 A personalized view into the information most relevant to you.



**Three-Year Warranty**  
[www.keysight.com/find/ThreeYearWarranty](http://www.keysight.com/find/ThreeYearWarranty)  
 Keysight's committed to superior product quality and lower total cost of ownership. Keysight is the only test and measurement company with three-year warranty standard on all instruments, worldwide. And, we provide a one-year warranty on many accessories, calibration devices, systems and custom products.



**Keysight Assurance Plans**  
[www.keysight.com/find/AssurancePlans](http://www.keysight.com/find/AssurancePlans)  
 Up to ten years of protection and no budgetary surprises to ensure your instruments are operating to specification, so you can rely on accurate measurements.

### Keysight Infoline

**Keysight Infoline**  
[www.keysight.com/find/service](http://www.keysight.com/find/service)  
 Keysight's insight to best in class information management. Free access to your Keysight equipment company reports and e-library.

**Keysight Channel Partners**  
[www.keysight.com/find/channelpartners](http://www.keysight.com/find/channelpartners)  
 Get the best of both worlds: Keysight's measurement expertise and product breadth, combined with channel partner convenience.

[www.keysight.com/find/n9067c](http://www.keysight.com/find/n9067c)